

Two-Wire Smoke/Heat Detectors F220 Series

Technical Service Note

December 2003

Two-Wire Detector/Control Panel Compatibility List



Bosch Security Systems makes no claims either written, oral, or implied that two-wire smoke detectors will work with any two-wire control panels except those listed in *Table 1*.

Table 1 is a list of control panels that are compatible with the following detectors:

- F220-P
- F220-PTH
- F220-PC
- F220-PTHC
- F220-135
- F220-135F
- F220-190F

Table 1: F220 Compatibility List

Manufacturer	Model	Zone Module	Maximum Detectors per Zone	Control Panel Manufacturer's Compatibility Identifier
Bosch Security Systems	D2212B/D2412U/D2812/D2812U	Built In	12	B
Bosch Security Systems	D4412/D6412	Built In	12	A
Bosch Security Systems	D7022	Built In (12 V Loop)	20	A
Bosch Security Systems	D7022	Built In (24 V Loop)	20	A
Bosch Security Systems	D7024	Built In	20	B
Bosch Security Systems	D7024	D7034	20	B
Bosch Security Systems	D7212/D7212G/D7212B1/D7412/D7412G	D125B	10	D125B
Bosch Security Systems	D9112/D9112B1/D9124/D9412/D9412G	D125B	10	D125B
Bosch Security Systems	DS7080i/DS7080iV2+/DS7080iP32	Built In	20	B
Bosch Security Systems	DS7220/DS7240	Built In	12	A
Bosch Security Systems	DS7400/DS7400X/DS7400Xi	Built In	20	B
Bosch Security Systems	DS7400/DS7400X/DS7400Xi	DS7433	20	B
Bosch Security Systems	DS9400/DS9400i/DS9400M	Built In	20	B
Bosch Security Systems	DS9400/DS9400i/DS9400M	DS9434	20	B
Bosch Security Systems	DS9422	Built In (12 V Loop)	20	A
Bosch Security Systems	DS9422	Built In (24 V Loop)	20	A
ADEMCO	Vista 15P	Built In	16	Zone 1
ADEMCO	Vista 20P	Built In	16	Zone 1
GE Interlogix	Concord Series	Built In	10	Concord
Honeywell	5800G	D125B	10	D125B
Honeywell	5900G	D125B	10	D125B



